




VMDTC25-20-M6-40-Z/10PK

10 pack

Ruland VMDTC25-20-M6-40-Z/10PK, Vibration Isolation Mount, 25mm OD, M6 Tapped Holes, 6mm Tapped Hole Depths, 20mm Height, 40 Shore A Natural Rubber Jacket, Steel



Description

Ruland VMDTC25-20-M6-40-Z/10PK is a 10 pack of vibration isolation mounts, each with two tapped holes. An individual isolation mount has a 25mm outside diameter, M6 tapped holes, 6mm tapped hole depths, and 20mm height. Vibration isolation mounts are used to dampen shock loads and reduce noise and wear on industrial equipment such as motors, conveyors, compressors, fans, or pumps which allows for a safer and more pleasant working environment. They are often referred to as a sandwich mount or rubber buffer because they function as a shock or vibration isolator sandwiched between two machine components or surfaces. A vibration isolation mount can be mounted to the system by threading it onto an existing stud on the components. The rubber jackets are made from natural rubber which has good elasticity and is well suited for most industrial equipment. Vibration isolation mounts in this pack have 40 Shore A hardness for high dampening and shock absorption. Bodies are made from zinc plated steel allowing for high strength suitability in most industrial applications. These vibration isolation mounts are manufactured by Otto Ganter, inventoried by Ruland, and RoHS3 compliant.

Product Specifications

Outer Diameter (OD)	0.98 in (25 mm)	Height (H1)	0.79 in (20 mm)
Thread (TH)	M6 x 1.0	Plate Thickness (PT)	0.08 in (2 mm)
Tapped Hole Depth (LT)	0.24 in (6.1 mm)	Spring Rate	445.39 lb/in (78 N/mm)
Shore Hardness	40A (+/- 5)	Max Deflection	0.20 in (5.0 mm)
Max Axial Load	87.68 lb (390 N)	Multipack Quantity	10
Geometry	Cylindrical	Rubber Material	Natural Rubber
Metal Material	Zinc Plated Steel	Metallic Body Finish	Zinc-Plated
Manufacturer	JW Winco/ Otto Ganter	Country of Origin	Hungary
Weight (lbs)	0.478800	UPC	634529359068
Tariff Code	4016.99.6000	UNSPC	31162804
Note 1	Performance ratings are for guidance only. The user must determine suitability for a particular application.		